Product data sheet

Specifications



Insulating mounting plate for enclosure H300xW250mm made of bakelite

NSYMB3025

Main

Range	PanelSeT
Accessory / separate part category	Mounting accessory
Product or component type	Mounting plate
Device application	Multi-purpose
Enclosure nominal dimensions	- H: 300 mm W: 250 mm
Mounting location	Direct fixing on backstuds Step slide
Mounting plate description	Plain
Range compatibility	PanelSeT S3D PanelSeT CRN PanelSeT PLM PLM
Quantity per set	Set of 1
Material	Bakelite
Colour	Black (RAL 9005)

Complementary

Fixing mode	Screwed on backstuds - screw type M8 By fixing element
Permanent permissible load	1875 kg
Height	265 mm
Width	200 mm
thickness	4 mm
Net weight	2 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	0.400 cm
Package 1 Width	20.000 cm
Package 1 Length	26.500 cm
Package 1 Weight	304.000 g

Contractual warranty

Warranty (in months)	18

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Environmental footprint

Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
SCIP Number	F0a7ce1b-1203-4036-ab50-52a050b14839
EU RoHS Directive	Compliant By Exemption
REACh Regulation	Reference contains Substances of Very High Concern above the threshold
California proposition 65	WARNING: This product can expose you to chemicals including: Lead, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

End of life manual availability	No need of specific recycling operations
Take-back	No